

IR15S-PC-RA12

Inductive Proximity Switch **3-Wire Ring Sensors** Operating principle: Static

Mind $O \neq 0$, $I \neq l \neq 1$, $S \neq 5$, $B \neq 8$.

Ring diameter Ø 15.1 mm Resolution adjustable, Ø >2 mm Operating voltage 10...30 V_{DC} Reverse polarity protection built-in Current consumption <10 mA Current load capability 200 mA Output function normally closed Output polarity **PNP** built-in, self-resetting <2 V @ 200 mA multi-turn potentiometer ≤35 m/s · ≤115 ft/s 0.5 ms | 10 ms -20...+70 °C · -3...+159 °F IP67 PA 6,6 PBT built-in

Short circuit protection Voltage drop Adjustment Object speed Response | release time Operating temperature Protection class Ring material Housing material Switching indicator Connection male connector M12 Complies with




C€, RoHS


RoHS

0 sensitivity M3×4 0 20

Wiring diagram



Pinout





Caution! This device shall not be used if the safety of persons rely on its faultless function.

 ${\tt XECRO}\ reserves\ the\ right\ to\ make\ minor\ changes\ without\ prior\ notification.$